

General Settings

General setting

When activating the chatbot and collecting information from the contact. you will execute a specific command by calling a link that contains these instructions, such as sending an email, the default value is `http://localhost/webhook.php`, if you do not care about this, you can leave it blank.

Default language: massejli can distinguish the contact's language through the words that the contact writes, and not through the letters only because there are common characters between the languages. Default. Never enter a language that you did not actually use in the list, as this may affect how well your system works.

Selecting the option to send to a list of numbers by default: On the page of sending a message, the option to send to a list of numbers will be activated by default, useful for the speed of work with the interface

Selecting the option to send to a contact list by default: On the Send a message page, the option to send to a number list will be activated by default, useful for the speed of work with the interface

Session duration: It is the period during which if the caller does not speak with the number, we consider the new speech as a session to collect new information for the chatbot and ignore the old information. The default value is 360 seconds, or 6 minutes.

menu icon: the emoji at the beginning of every line in the list.

End conversation code: It is the code that if the contact sends it, it ends the conversation, but the conversation bot will re-show its main list when the contact sends any other word, its default value is 999

The bot stop code: The contact who wants to talk to a normal person can stop the chatbot and the list by sending this code, this is how you talk to him instead of the bot, the default value for the bot stop code is xxx

menu interval time: When the contact speaks with the number, for the first time, the list will appear to him, so as not to disturb him by showing it with every message he sends, because a period is required if he does not speak with the number and show it to him again This period in seconds is preferably 129600 seconds.

Time format:

% Y Symbol of the year

% m Month Symbol

% d Symbol of the Day

% H Clock icon

% M is the minute symbol

General Settings

% S Second Symbol

auto replay delay: for the bot to work like a normal person, and the contact does not respond quickly, it must be delayed by a few seconds. You can set it to zero so that it is never delayed.

menu return command: When the visitor sends a sublist command and wants to re-order the main list for the list, he sends this code, by default it is 000.

Do not forget to click on the Save button to save the settings

Unique solution ID: #1131

Author: Massejli Support

Last update: 2021-06-18 11:01